PRODUCT DATA SHEET

WELLING AND CROSSLEY

WC-P7750H • 811992

CONSTRUCTION SITES | DIY WORKSHOP | HOME BACKUP | OUTDOOR EVENTS | MARKET STALLS MOBILE BUSINESS | LIGHT AGRICULTURE | AGRICULTURE

POWERED by HONDA

HONDA AUSTRALIA APPROVED

3 YEAR WARRANTY — Engine

2 YEAR WARRANTY — Alternator and Frame

PRODUCT DETAILS

The Welling and Crossley P7750H is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is powered by the tried and proven Honda GX390 motor. The WC-P7750H packs a lot of power in a compact footprint.

APPLICATIONS

- DIY workshops to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems, etc.
- Mobile businesses or market stalls for powering appliances*

  **Ensure generator noise levels comply with site-specific requirements and local regulations.*

FEATURES

- 2 x IP66 outlets (single phase – 15 Amp)
- USB-A and USB-C outlets
- Multiple start options: Recoil start, push-button electric start, 2-wire remote start
- Transport kit included: Fold-out, wheelbarrow-style handle and large wheels
- Powerful & efficient: Air-cooled OHV 4-stroke engine with transistor magneto ignition
- Digital V/F/T Display (Volts, Frequency, Time)
- Transistorised ignition
- Overload alarm, output indicator
- 2-year Welling and Crossley frame and alternator warranty (battery excluded)
- 3-year Honda engine warranty

TECHNICAL DATA

MODEL RATING	7.75kVa with AVR
POWER FACTOR	0.8
MAX. AC OUTPUT	6000 W
RATED AC OUTPUT	5500W Max. 15A
RATED MOTOR SPEED	3000 rpm
RATED VOLTAGE	230/240VAC 1ph / 50Hz
ENGINE MODEL	Honda GX390
ENGINE TYPE	Single cylinder, 4 stroke, OHV, air-cooled petrol
DISPLACEMENT	389cc

OIL	1.1 litres SAE10W-30
SPARK PLUG	NGK BPR6ES
NOISE LEVEL @ 7M	89 dBA
FUEL TYPE	Petrol – 91 octane unleaded
FUEL TANK CAPACITY	6.1 L
FUEL CONSUMPTION	Approx. 1.37L/hr @ 1/4 load
PACKAGING (L X W X H)	705 x 555 x 590mm
PRODUCT (L X W X H)	550 x 700 x 660mm
DRY WEIGHT	80 kg